

INTRUDER ALARM

PERIPHERALS AND EXPANSIONS

1/2



RF32VEDO

RF TRANSCEIVER MODULE, 32 CHANNELS



Radio transceiver modules which allow use of the wireless devices listed in Comelit VEDO series control panels. They allow the use of up to 32 sensors, 16 sirens and 32 remote radio controls. Housed in a white flame-resistant plastic container, complete with anti-opening and anti-tear tamper systems that can be isolated. It can also be housed inside containers art. BOXPLASTIC, BOXMETAL and BOXFLUSH. Dimensions (W x H x D) $126 \times 80 \times 32$ mm.



Operating temperature (°C)

INTRUDER ALARM

PERIPHERALS AND EXPANSIONS





RF32VEDO

RF TRANSCEIVER MODULE, 32 CHANNELS	
MAIN FEATURES	
Wireless technology	Bidirectional protocol
Radio frequency band (MHz)	868.05 ÷ 869.95
Bus type of connections	RS485
Maximum number of wireless sensors (n°)	32
Maximum number of sirens (n°)	16
Number of radio controls (n°)	32
Two-way radio	Yes
Compatible control panels	VEDO
HARDWARE SPECIFICATIONS	
Height (mm)	80
Width (mm)	126
Depth (mm)	32
Plastic container	Yes
Colour	White

-10 ÷ 55